CR03AM

LOW POWER USE

NON-INSULATED TYPE, GLASS PASSIVATION TYPE

CR03AM

- $I_{T\ (AV)}$ 0.3A
- V_{DRM} 400V/600V
- I_{GT} 100μA

OUTLINE DRAWING

Dimensions in mm



JEDEC : TO-92

APPLICATION

Leakage protector, timer, gas ignitor

MAXIMUM RATINGS

Symbol	Parameter	Voltage class		Unit
		8	12	
V_{RRM}	Repetitive peak reverse voltage	400	600	V
V_{RSM}	Non-repetitive peak reverse voltage	500	800	V
$V_{R\ (DC)}$	DC reverse voltage	320	480	V
V_{DRM}	Repetitive peak off-state voltage *1	400	600	V
V_{DSM}	Non-repetitive peak off-state voltage *1	500	800	V
$V_{D\ (DC)}$	DC off-state voltage *1	320	480	V

Symbol	Parameter	Conditions	Ratings	Unit
$I_{T\ (RMS)}$	RMS on-state current		0.47	A
$I_{T\ (AV)}$	Average on-state current	Commercial frequency, sine half wave, 180° conduction, T_a=47°C	0.3	A
I_{TSM}	Surge on-state current	60Hz sine half wave 1 full cycle, peak value, non-repetitive	20	A
I^2t	I^2t for fusing	Value corresponding to 1 cycle of half wave 60Hz, surge on-state current	1.6	A^2s
P_{GM}	Peak gate power dissipation		0.5	W
$P_{G\ (AV)}$	Average gate power dissipation		0.1	W
V_{FGM}	Peak gate forward voltage		6	V
V_{RGM}	Peak gate reverse voltage		6	V
I_{FGM}	Peak gate forward current		0.3	A
T_j	Junction temperature		–40 ~ +110	°C
T_{stg}	Storage temperature		–40 ~ +125	°C
—	Weight	Typical value	0.23	g

*1. With gate to cathode resistance R_{GK}=1kΩ.

MITSUBISHI ELECTRIC

CR03AM

LOW POWER USE
NON-INSULATED TYPE, GLASS PASSIVATION TYPE

ELECTRICAL CHARACTERISTICS

Symbol	Parameter	Test conditions	Limits			Unit
			Min.	Typ.	Max.	
I_{RRM}	Repetitive peak reverse current	T_j=110°C, V_{RRM} applied	—	—	0.1	mA
I_{DRM}	Repetitive peak off-state current	T_j=110°C, V_{DRM} applied, R_{GK}=1kΩ	—	—	0.1	mA
V_{TM}	On-state voltage	T_a=25°C, I_{TM}=4A, instantaneous value	—	—	1.8	V
V_{GT}	Gate trigger voltage	T_j=25°C, V_D=6V, I_T=0.1A *3	—	—	0.8	V
V_{GD}	Gate non-trigger voltage	Tj=110°C, V_D=1/2V_{DRM}, R_{GK}=1kΩ	0.2	—	—	V
I_{GT}	Gate trigger current	T_j=25°C, V_D=6V, I_T=0.1A *3	1	—	100*2	μA
I_H	Holding current	T_j=25°C, V_D=12V, R_{GK}=1kΩ	—	1.5	3	mA
$R_{th\ (j-a)}$	Thermal resistance	Junction to ambient	—	—	180	°C/W

*2. If special values of I_{GT} are required, choose at least two items from those listed in the table below. (Example: AB, BC)

Item	A	B	C
I_{GT} (μA)	1 ~ 30	20 ~ 50	40 ~ 100

The above values do not include the current flowing through the 1kΩ resistance between the gate and cathode.

*3. I_{GT}, V_{GT} measurement circuit.



SWITCH 1 : I_{GT} measurement
SWITCH 2 : V_{GT} measurement
(Inner resistance of voltage meter is about 1kΩ)

PERFORMANCE CURVES

MAXIMUM ON-STATE CHARACTERISTICS



RATED SURGE ON-STATE CURRENT



MITSUBISHI ELECTRIC

CR03AM

LOW POWER USE

NON-INSULATED TYPE, GLASS PASSIVATION TYPE

GATE CHARACTERISTICS



GATE TRIGGER CURRENT VS. JUNCTION TEMPERATURE



GATE TRIGGER VOLTAGE VS. JUNCTION TEMPERATURE



MAXIMUM TRANSIENT THERMAL IMPEDANCE CHARACTERISTICS (JUNCTION TO AMBIENT)



MAXIMUM AVERAGE POWER DISSIPATION (SINGLE-PHASE HALF WAVE)



ALLOWABLE AMBIENT TEMPERATURE VS. AVERAGE ON-STATE CURRENT (SINGLE-PHASE HALF WAVE)



MITSUBISHI ELECTRIC

CR03AM

LOW POWER USE

NON-INSULATED TYPE, GLASS PASSIVATION TYPE

MAXIMUM AVERAGE POWER DISSIPATION (SINGLE-PHASE FULL WAVE)



ALLOWABLE AMBIENT TEMPERATURE VS. AVERAGE ON-STATE CURRENT (SINGLE-PHASE FULL WAVE)



MAXIMUM AVERAGE POWER DISSIPATION (RECTANGULAR WAVE)



ALLOWABLE AMBIENT TEMPERATURE VS. AVERAGE ON-STATE CURRENT (RECTANGULAR WAVE)



BREAKOVER VOLTAGE VS. JUNCTION TEMPERATURE



BREAKOVER VOLTAGE VS. GATE TO CATHODE RESISTANCE



MITSUBISHI ELECTRIC

CR03AM

LOW POWER USE

NON-INSULATED TYPE, GLASS PASSIVATION TYPE

BREAKOVER VOLTAGE VS. RATE OF RISE OF OFF-STATE VOLTAGE



HOLDING CURRENT VS. JUNCTION TEMPERATURE



HOLDING CURRENT VS. GATE TO CATHODE RESISTANCE



REPETITIVE PEAK REVERSE VOLTAGE VS. JUNCTION TEMPERATURE



GATE TRIGGER CURRENT VS. GATE CURRENT PULSE WIDTH



MITSUBISHI ELECTRIC